

**Listing of the Claims:**

Claims 1 – 9 (Cancelled).

Claims 10-51 (Cancelled)

52. (New) A phased array for controlling a radiation pattern comprising:  
an extended resonance circuit having an N plurality of ports;  
an antenna and a shunt impedance connected to each port;  
the extended resonance circuit including a plurality of first tunable impedances, one of which is connected between each of the N plurality of ports, each first impedance transforming the admittance of one port coupled to the first tunable impedance to the conjugate of the admittance for a serially adjacent second one of the N plurality of ports such that the voltage at each of the ports is the same magnitude across the circuit; and  
a power source having an impedance matched to the impedance of an endmost port in the array.

53. (New) The phased array of claim 52 wherein each of the first plurality of impedances is a tunable inductor.

54. (New) The phased array of the claim 53 wherein the series impedance between each port is a tunable transmission line, and the shunt impedance is a tunable capacitance.

55. (Currently Amended) The phased array of claim 52 wherein each of the plurality of first impedances between each port includes two serially connected quarter-wave transformers with a tunable capacitor connected in shunt therebetween.

56. (New) The phased array of claim 52 further comprising:  
a single biased voltage applied to the endmost port in the array.
57. (New) The phased array of claim 52, wherein the phase shift between successive ports is equal.